

# Senseair LP8

## Sensor module for battery-powered applications.

Senseair LP8 is a miniature sensor module which targets battery-powered applications. It gives customer a full control on sensor integration into a host system, flexibility in changing of the CO<sub>2</sub> measurement period and consequently power consumption. One measurement requires only 3.6mC of charge (or energy 11.9mJ at 3.3V battery supply). The sensor is supposed to be switched off between measurements to minimise power consumption.

A wide 2.9 to 5.5V supply voltage range enables long duty if sensor is powered from three alkaline 1.5V batteries. A compact alternative is to power sensor from a single 3.6V Li-SOCI2 battery.

The LP8 provides a communication protocol which allows customer changing measurement period on the fly and control ABC (Automatic Baseline Correction) period. Background and zero calibrations are implemented.



### Standard specification

Operating principle	Non-dispersive infrared (NDIR)
Measurement range [CO <sub>2</sub> ]	0–2000ppm
Operation range	0–50°C, 0–85%RH non condensing
Accuracy [CO <sub>2</sub> ]	±50ppm ±3% of reading <sup>1,2,3</sup>
Power supply	2.9–5.5V
Peak current	125mA @ 25°C
Shutdown current	1µA <sup>4,5</sup>
Average current	
16s measured period	245µA <sup>4,5</sup>
60s measured period	66µA <sup>4,5</sup>
120s measured period	31µA <sup>4,5</sup>
Measurement period	≥16s
Dimensions max.	33.5 x 19.9 x 12.5mm
Sensor lifetime expectancy	>15 years
Communication	2.5V UART logic (host-slave protocol)

### Key benefits

- 3.6mC per measurement (11.9mJ @ 3.3V)
- Miniature size (Senseair® S8 format)
- A wide supply voltage range enables a variety of battery options
- Adjustable measurement period by host
- Adjustable ABC period by host



Note 1: Accuracy is met at 10 – 40°C, 0 – 60%RH, after minimum three (3) performed Automatic Baseline Corrections, preferably spanning eight (8) days in-between, or a successful zero calibration.  
 Note 2: Based on reading filtered CO<sub>2</sub> measurement data in stable environments and in continuous operation by control mode.  
 Note 3: Accuracy specification is referred to calibration gas mixtures with additional uncertainty of ±1%.  
 Note 4: Resistor network for measuring VCAP voltage adds 14µA @ 5.5V.  
 Note 5: External super-capacitor leakage is not considered.

# Senseair LP8 Technical Specification

## General Sensor Performance:

Required storage/operation environment	Non-corrosive and non-condensing <sup>1</sup>
Sensor lifetime expectancy	>15 years
Service interval and maintenance	Adjustable ABC period by host <sup>1</sup>
Self-diagnostics	Complete function-check of the sensor module every power ON.
RMS Noise CO <sub>2</sub>	14ppm @ 400ppm @ 25°C 25ppm @ 1000ppm @ 25°C

Operative environment required for keeping calibrated and specified accuracy in gas measurement:

Operative temperature range	0–50°C
Operative relative humidity range	0–85%RH, non-condensing <sup>1</sup>

## Electrical Properties:

Power supply	2.9–5.5V
Peak current	140mA maximum @ 0°C (typical 125mA @ 25°C)
Shutdown current	1µA
Charge per measurement	3.6mC (3.9mC worst case)
Energy per measurement	11.9mJ @ 3.3V

## Mechanical Properties:

Electrical Connections	VCAP, VBB and GND
Dimensions max.	33.5 x 19.9 x 12.5 mm (Length x Width x Height)

## CO<sub>2</sub> Measurement:

Operating principle	Non-dispersive infrared (NDIR)
Measurement Range	0–2000ppm CO <sub>2</sub>
Accuracy	±50ppm ±3% of reading <sup>2</sup>
Measurement period	≥16s, adjustable by host

## Temperature Measurement:

Operating principle	NTC (Negative Temperature Coefficient) Resistor
Measurement range	0–50°C
Accuracy	±0.7°C
Measurement interval	Adjustable by host

Note 1: When using ABC (Automatic Baseline Correction) algorithm of Senseair.

Note 2: Specification is referenced to uncertainty of calibration gas mixtures ±1%. Accuracy is met at 10 to 40°C, 0 to 60%RH, after three ABC periods, each period followed by ABC command set in the Calculation Control byte.